



**In the Box:**



4.5 TRANSFORMER



CALL POINT RESET KEY

**PRODUCT INFORMATION:**

- Mains Powered Only
- Screen resolution: 480×272
- Connect 250 Devices
- Secure Pairing
- First Aid Call function
- System Status Indication
- Engineers Mode
- Supervisors Mode
- 85dB Buzzer
- Fast Pair (V3 Software version only)
- Auto Site Reset Function
- Mesh Radio connectivity
- Radio Frequency 869Mhz
- Zoning Function
- Optional Battery Backup (Separate Device)
- Colour coded squares for easy device identification
- Manual Call Point for easy Activation
- Wall or Desk Mount Configuration

EN54 Compliant Call Point

<b>Product Code:</b>	<b>FMCEVASYNP2</b>
<b>IP Rating:</b>	<b>Indoor Only</b>
<b>Total Weight:</b>	<b>1KG</b>
<b>Overall Dimmensions:</b>	<b>H 225 X W 166 X D 75MM</b>
<b>Sound Output (dB)</b>	<b>85dB</b>

